

 **WARNING****PLEASE READ ALL INSTRUCTIONS BEFORE ATTEMPTING INSTALLATION**

- To prevent personal injury or product damage, only licensed electricians should install.
- To avoid electric shock or component damage, disconnect power before attempting installation or servicing.
- This product must be installed in accordance with the national electric code (NEC) and all applicable federal, state and local electric codes and safety standards.
- Disconnect product and allow cooling prior to servicing.
- Any alteration or modification of this product is expressly forbidden as it may cause serious personal injury, death, property damage and/or product malfunction.
- To prevent wiring damage or abrasion, do not expose wiring to edges of sheet metal or other sharp objects.
- This device is not intended for use with emergency exits.
- **CAUTION:** Connect fixture to a 120 Volt, 60Hz power source only. Any other connection void the warranty.
- Suitable for damp locations.

LIST OF RECOMMENDED DIMMERS**LUTRON:** TGCL-153P, MACL-153M, CTCL-153P, PD-6WCL**LEVITON:** IPL06-10Z, 6672-1LW, 6674-POW, DLS06-1LZ

Installation

1. Before beginning installation, remove the luminaire and accessories package from the carton, Remove the plastic lens from the luminaire by rotating the lens until it free from the metal housing.
2. Turn off power at the circuit breaker or electrical box before starting installation.
3. Thread the enclosed mounting screw into the junction box mounting holes, and partially tighten the screws
4. Pull the power supply wires out from the junction box. Using wiring nuts connect the black supply wire (hot) to the black luminaire wire, the white supply wire (neutral) to the white luminaire wire, and the supply ground wire to the green luminaire wire, wrap all wire connections with electrical tape for a secure connection.
5. After all connected wire are secured, install the metal luminaire housing to the junction box by sliding the housing keyhole slot over the mounting screws. Rotate the luminaire housing clockwise until the screw slides into the narrow ends of the keyhole slots. Tighten the mounting screws to secure the metal housing is in place.
6. Reattach the plastic lens to the luminaire housing by rotating the lens until the lens fit securely in place.
7. When the installation is completed, the luminaire should appear flush to the ceiling and turn on power to check the fixture is in working order.

