



TrueFit™ Ballast Compatible 18W LED Tube

DESCRIPTION: LED Tube T8 18W 4FT
ITEM NUMBER: 834118-XX-B-F / 834018-XX-B-C

FEATURES

Revolutionary ballast-compatible LED T8/T12 fluorescent replacement works with most existing ballasts for a truly easy replacement process. TrueFit™ LED replacement tubes include an internal power supply - after the existing fluorescent ballast fails, simply by-pass the ballast and rely on the internal driver for continued use. High-efficiency solid state LED array, advanced heat sink and optical diffuser, 50%+ savings in energy consumption, minimum 50,000 hour life, 120-277V compatible, shock & vibration resistant, mercury free. UL and DLC listed.

APPLICATIONS

- | | |
|---------------|---------------------------------------|
| Offices | Buses |
| Classrooms | Trains |
| Lobbies | Warehouses |
| Back-of-house | Parking Lots |
| Restaurants | Retail Displays |
| Malls | Backlighting for Square Billboards |
| Hotels | Backlighting for Advertisement Boards |



REPLACES



T8 / T12 (G13) Fluorescent Tubes

TECHNICAL PARAMETERS

Life Span: 50,000
Fixture Material: Aluminum Profile & PC Cover
IP Rating: N/A
Dimensions: 26x1200mm (1.02x47.24in)
Dimmable: Yes
Weight: 365 g (0.80 lbs)
Thermal Layer Material: Aluminum Profile
Operating Temperature : -35°C~50°C

OPTICAL PARAMETERS

LED Chip Type: SMD
LED Chip Quantity: 120
Lumens: 2070
Color Temperature: 5000K (50)
 4000K (40)
 3500K (35)
CRI:Ra ≥ 80
Beam Angle: 180°
Socket: G13
Cover: Clear or Frosted

ELECTRICAL PARAMETERS

Input Voltage: 120~277 VAC
Total Power Consumption: 18W
Power Factor: > .90



Due to advancements in technology, specifications are subject to change without notice.

All images are copyright Truly Green Solutions, Inc. and may be only be used with permission.

WARNING: READ INSTRUCTIONS BEFORE INSTALLING

Disconnect all power sources to the fixtures before installing.



Ordering Information – TrueFit™ 15W 4'

834015-50-B-C TrueFit™ Ballast Compatible 15W LED Tube (5000K) Clear

834115-50-B-F TrueFit™ Ballast Compatible 15W LED Tube (5000K) Frosted

834015-40-B-C TrueFit™ Ballast Compatible 15W LED Tube (4000K) Clear

834115-40-B-F TrueFit™ Ballast Compatible 15W LED Tube (4000K) Frosted

834015-35-B-C TrueFit™ Ballast Compatible 15W LED Tube (3500K) Clear

834115-35-B-F TrueFit™ Ballast Compatible 15W LED Tube (3500K) Frosted

Ordering Information – TrueFit™ 18W 4'

834018-50-B-C TrueFit™ Ballast Compatible 18W LED Tube (5000K) Clear

834118-50-B-F TrueFit™ Ballast Compatible 18W LED Tube (5000K) Frosted

834018-40-B-C TrueFit™ Ballast Compatible 18W LED Tube (4000K) Clear

834118-40-B-F TrueFit™ Ballast Compatible 18W LED Tube (4000K) Frosted

834018-35-B-C TrueFit™ Ballast Compatible 18W LED Tube (3500K) Clear

834118-35-B-F TrueFit™ Ballast Compatible 18W LED Tube (3500K) Frosted